PC CADDIE cash register on iPod Touch 5G or iPhone 5

The PC CADDIE handheld POS system can now also be conveniently used on the iPod/iPhone/iPad:



This requires the iTap RDP software, which should be configured as follows:

First, the software must be downloaded and installed from the Apple Store, then the iPod's home screen can look like this, for example:



Configure iTap RDP

Firstly, a "bookmark" must be created to access the server. This is usually done via "Add manual bookmark" - the entry "Handheld 1" has already been created here. If an entry already exists, tap the arrow on the right to adjust the configuration if necessary.

iPod		(e) 100
0	Type name or address to find comput	
Se	earch Results	
	No Search Results	
	Bookmarks	
	iTap mobile RDP Testser	0
0	demo.pccaddie.com	0
0	Handheld 1	0
	Osemame: GOLF (Handheid I	-
	Add Manual Bookmark	>
•	Global Settings	
	Settings	>
	Extensions	>
	Set Lock Code	>

The "Label" can be freely selected for the other settings - host, port and gateway (a gateway is rarely used) should be specified by the administrator of the IT environment.

Pod 🤤 13:05	5 🕀 📾
Cancel Bookn	hark Save
Host	
Label:	Handheld 1 >
Host:	
Port	Default >
Use System Proxy:	\bigcirc
Gateway:	>
 TS Gateway ser TS Gateway sec Credentials 	ver is reachable curity
Credentials: GO	LF\Handheld1 >
Store Credentials:	
Settings	

If you scroll further down, the resolution for "Screen" is particularly important, and "Remember Zoom" should also be activated:

Pod 🗢 13	3:05 🕒 I	
Cancel BOO	kmark Sa	•
Use System Proxy	v: 🔿 🔿	
Gateway:	· · · · · · · · · · · · · · · · · · ·	·
 TS Gateway s TS Gateway s Credentials 	server is reachable security	
Credentials: G	OLF\Handheld1 >	•
Store Credentials	:	
Settings		
Screen:	272x480x16 >	•
Remember Zoom	•	
Advanced	>	·

The option to enter a customised screen resolution can be found at the bottom under "Screen":

iPod Ģ	13:05	() ISH
Bookmark	Screen	
Normal (10)24x768)	
720p (1280	x720)	
Large (128	0x960)	
Larger (128	80x1024)	
Portrait (96	60x1440)	
Landscape	e (1440x960)	
Huge (1600	0x1200)	
1080p (192	0x1080)	
Full HD (19	20x1200)	
Retina (204	48x1536)	
Custom (2	72x480)	~

Under "Advanced", no adjustments need to be made to the upper points at first...

iPod 🤤	13:06	9 100
Bookmark Ad	vanced	
Connection		
Console:	$\bigcirc \circ \bigcirc$	
Sound:	Play on Device	>
Performance		>
Keyboard:	Automatic	>
Security Level	NLA	>
Automatic Rec	connect: 30 Min	>
VDI Informatio	n empty	>
Remote Progra	am:	>
User Interface		
Border:	Off	>
		_

...further down, however, the "Utility Bar" setting must be set to "Initially Off" and, above all, the "Mouse Mode" must be set to "Draw Mode":

Pod 🗢	13:06		۱	
Bookmark	Advanc	ed		
VDI Informa	tion	emp	oty >	1
Remote Pro	gram:		>	·
User Interfa	се			
Border:		(Off >	
Status Bar:		$\bigcirc \circ$)	
Utility Bar:		Initially (Off >	
Mouse Mod	le:	Draw Mo	de >	
Swap Mouse	Buttons:	$\bigcirc \circ$)	
Sticky Modif	iers:	$\bigcirc \circ$)	
Reduce Lag (at cos	t of throu	$\bigcirc \circ$)	
Connection	Tests:)	

In the further "Global Settings" (accessible from the iTap RDP main menu), the gateways are stored if required. It can be useful to define the previously defined connection as "Autostart" here - then simply less can "go wrong".



Use cash register

It is now easy to start the PC CADDIE cash register dial-in. PC CADDIE then appears with the customer list of the cash register, preceded by the password prompt if necessary. If you tap the screen briefly with three fingers at the same time, the "Utility Bar" appears at the top:

Help 🏭 🔨 🚺 💷 🐗
Tisch/Gest Buchungen Funktionen
Filter 🗖 Bediener 🔽 Kasse 🛛 Tisch
Tisch 22 5,50 seka
Tisch/Gast (FS
QWERTZUIOPÜß
ASDFGHJKLÖÄ·
Y X C V B N M [] . 0 🖾

The first time you use it - after you have dragged the screen image to the correct size once - you should block any further resizing with the lock icon at the top.

You will also find the following symbols from left to right:

- Call up help (probably not so important for end users)
- Show keyboard (can also be done by swiping down with three fingers but our keyboard is probably better here, it actually works quite well...)
- **Draw mode** It is important that this is set. There may be two other symbols here, but they are unsuitable for handheld operation. If the operation seems to be delayed, it is often due to this.
- Lock zoom
- Option if you have several screens not important for us
- **Disconnect the connection** especially if you have activated Autostart and want to return to the configuration.

Further operation is as generally described!